

# HYBRID CONTROL PANEL

WIRED / WIRELESS

# X64



**Bidirectional wireless system**

Voice support 

Radio range 1 km

BUS line (4 wires) RS485



**64** wireless / wired zones

**56** programmable wireless devices on board


**56** programmable wireless devices with second wireless expansion

**GPRS** or **3G** modules on board

**868 MHz** or **916 MHz** frequency



CMS multiformat




Clamps removable



iOS/Android APP  
**AMCMANAGER**





Settable by PC



Technical Features	X64
<b>WIRED ZONES ON BOARD</b>	8
<b>WIRELESS DEVICES ON BOARD</b>	32 devices 20 remote controls 4 sirens
<b>WIRELESS / WIRED ZONES</b>	64 (for wired zones with expansions or keypads)
<b>OUTPUTS</b>	2 on board expandable to 14 (with expansions or keypads)
<b>USER CODE</b>	64 users
<b>AREAS</b>	8
<b>GROUPS</b>	4
<b>KEYPAD</b>	8
<b>TAG READER</b>	8
<b>LOG EVENTS</b>	1000
<b>PHONE NUMBERS</b>	8 for SMS and private calls + 8 for CMS
<b>CARRIERS</b>	GPRS / 3G
<b>REMOTE MANAGEMENT GPRS/3G</b>	by App (iOS - Android)
<b>REMOTE PROGRAMMING GPRS/3G</b>	by PC software
<b>TIMERS</b>	8 per day week

The **X64** is security control panel for building protection; hybrid system (wired and wireless input). The control panel has audio support on board and it's equipped of 8 wired zones on board expandable to 64 with expansion module KX-in. The control panel has an integrated radio receiver on which it is possible to program 32 wireless devices, 20 remote controls and 4 wireless sirens. The control panel support 64 wireless devices. X64 is able to notify one or more situations of ALARM, ROBBERY, TAMPERING and TROUBLE with different carriers:

**GPRS/3G**

(voice call, SMS, Contact ID, DC09 IP protocol for Contact ID and SIA IP).

The panel can be controlled by the App AMC MANAGER (iOS / Android).

The programming can be made by keypad and/or PC software via USB cable and remotely via Cloud.

	2G	3G	3G	3G	AMC WIRELESS 868 MHz	AMC WIRELESS 916 MHz
GSM/GPRS/EDGE	850/900/1800/1900 MHz	900/1800 MHz	850/900/1800/1900 MHz	850/900/1800/1900 MHz		
UMTS/HSDPA		900/2100 MHz	850/1900 MHz	850(800)/2100 MHz		
<b>Codes:</b>						
<b>X64-2E8</b>	✓				✓	
<b>X64-3E8</b>		✓			✓	
<b>X64-3A8</b>			✓		✓	
<b>X64-3J9</b>				✓		✓