

DS-PDMCS-EG2-WE(B) Wireless Slim Magnet Detector



DS-PDMC-EG2-WE is a wireless opening detector that notifies of first signs of room intrusion by means of a broken door or window. It can be mounted on all types of doors including metal base and the onboard inputs will allow user to extend applications by wiring to different wired sensors.

- Slim design for an unobtrusive (unnoticeable) installation
- Fully remote configurable through APP
- Multiple enrollment methods and easy installation design
- Frequency hopping against jamming for reliable transmission



Specification

Specification				
Detection Performance				
Detection Method	Opening Contact			
Detection Gap	43 mm Max			
Feature				
Digital Processing	Support			
Tamper Protection	Front,Rear			
Environment Temperature	Support			
Indicator	συμμοτί			
Signal Strength Indicator	Support			
Interface				
Alarm Input	Normally Closed, Normally Open, Impulse Count			
Power Switch	Power up enrolling			
LED Indicator	Blue (alarm)			
Transmission				
Transmission Technology	Tri-X Wireless			
Transmission Method	Two-Way RF Wireless			
Transmission Frequency	868MHz			
Transmission Security	AES-128 Encryption			
Transmission Range(Free Space)	1.6Km			
Frequency Hopping	Support			
Enrolling Method	Power up,Remote ID,QR Code			
Electrical Characteristics				
Standard Battery Life	Up to 5 years (standby time)			
Power Supply	Battery powered			
Battery Type	CR2450 x 1			
Typical Voltage	3V			
General				
Operation Temperature	-10°C to 55°C (14°F to 131°F)			
Storage Temperature	-20°C to 60°C (-4°F to 140°F)			
Operation Humidity	10% to 90%			
Dimension(WxHxD)	24mm × 104mm × 24.4mm			
טוווופוואטוו(wxuxn)	13 mm × 34.4 mm × 11.4 mm			
Weight	59 g			
Application Scenario	Indoor			

Available Model

DS-PDMCS-EG2-WE(B)



Accessory

Optional

DS-PDP-IN-CR123A Indoor Detector Battery	DS-PWA96-Kit-WE AX PRO Kit (868MHz)	DS-PWA96-Kit-WB AX PRO Kit (433MHz)	DS-PDB-MC- Adapter Magnetic Contact Adapter	DS-PWA96-Kit1-WE AX PRO Kit (868MHz)
+ CR123A 3.0V -				00 - 1-1.
DS-PWA96-Kit2-WE AX PRO Kit (868MHz)	DS-PDB-MC-Brown Magnetic Contact Brown Housing	DS-PDB-MC- Brown(B) Magnetic Contact Brown Housing		
	• • • • • • • • • • • • • • • • • • •			



Headquarters No.555 Qianmo Road, Binjiang District, Hangzhou 310051, China T +86-571-8807-5998 www.hikvision.com

Follow us on social media to get the latest product and solution information.





HikvisionHQ



HikvisionHQ



Hikvision Corporate Channel



6 hikvisionhq